



The 10K Range of Toko Inductors have become popular for HF radio construction. The most commonly used types are listed below. The table indicates the number of turns - useful for seeing the turns ratio on the inductors. The total inductance in uH is given for the main winding.



TOKO PART	1-2	2-3	1-3	4-6	L	Q	Use
BKANK3333R	14	41	55	14	45uH	60	SW1 RF
BKANK3334R	7	11	18	3	5.5uH	85	SW2 RF
BKXNK3335R	4	4	8	2	1.2uH	85	SW3 RF/Ant
KXNK3767EK	2	6	8	5	1.2uH	80	SW1 RF Hi-Z
BKANK3426R	3	48	51	4	38uH	65	SW1 osc
KANAK3337R	2	25	27	3	5uH	50	SW2 osc
MKANK3428R	2	10	12	3	1.1uH	60	SW3 osc
KXNK4173AO			15		3uH	80	9MHz CIO