



TOKO 10K INDUCTORS FOR HF BAND USE

Revd. George Dobbs G3RJV

The 10K Range of Toko Inductors have become popular for HF radio construction. The most commonly used types are listed below.



TOKO PART	1-2	2-3	1-3	4-6	L	Q	Use
BKANK3333R	14	41	55	14	45uH	60	SW1 RF
BKANK3334R	7	11	18	3	5.5	85	SW2 RF
BKXNK3335R	4	4	8	2	1.2	85	SW3 RF/Ant
KXNK3767EK	2	6	8	5	1.2	80	SW1 RF Hi-Z
BKANK3426R	3	48	51	4	38	65	SW1 osc
KANAK3337R	2	25	27	3	5	50	SW2 osc
MKANK3428R	2	10	12	3	1.1	60	SW3 osc
KXNK4173AO			15		3uH	80	9MHz CIO

At the time of writing, the inductors are available in the UK from BONEX 12 Elder Way Langley Business Park Slough Berkshire SL3 6EP Tel: 01753 549502 Fax: 01753 543812. A suggested US supplier for designated TOKO coils is PENSTOCK [800] 736-7862

Title: TOKO 10K inductors for hf band use

Author: Revd. George Dobbs G3RJV
Page 1 of 1



GQRP Club
Datasheet